GEEK SHEET

WilsonPro A1000

Signal Booster Kit for Offices

WILSONPRO™

A1000

The WilsonPro A1000 (50 Ohm) from Wilson Electronics is the most popular commercial cell phone signal booster we currently offer. It features automatic gain control with a self- optimizing design for easy installation & maintenance.

- Boosts 3G & 4G for any home or building up to 1,000m2
- Most popular booster for large office buildings and warehouses
- Works for any phone using Major Network providers in Africa
- Complete kit: all parts included, easy install
- Better voice, text & internet guaranteed



ELECTRICAL SPEC

Item No.	A1000			
Frequency Bands	MHz dB	880-915 /925-960	1710-1785 / 1805-1880	1920-1980 / 2110-2170
Gain UL/DL	Ohm	70	74	80
Impedance	V and A	50		
Input Power		5 V / 4 A		

MECHANICAL SPEC

Connector Type		N-Female		
Dimensions	cm	22.23 x 21.59 x 5.72		
Weight	kg	0.88		
Booster Colour		Black		
		2100 MHz Band Uplink | Downlink	1800 MHz Band Uplink | Downlink	900 MHz Band Uplink | Downlink
Down Link Output Power	MAX	- | 25 dBm	- | 25 dBm	- | 25 dBm
	MIN	- | -5 dBm	- | -5 dBm	- | -5 dBm
Up Link Output Power	MAX	30dBm | -	30dBm | -	30 dBm- | -
	MIN	0 dBm | -	0 dBm | -	0 dBm | -

With up to +74 dB gain of power, it greatly enhances 4G LTE and 3G cell service for all your wireless cellular devices (smartphones, tablets, notebooks, hotspots, etc.) on any network provider in Africa. There are no monthly fees nor does it need to be connected to any internet source (Wi-Fi or landline) to work. It simply amplifies your existing in- building cellular service up to 32X for better voice, text, and faster internet. Backed by a 2-year manufacturer warranty, technical support team in Africa, 30-day better signal or money back guarantee, and lifetime technical support.

Goodbye, no-signal frustrations.